


PRAIRIE LABS, INC.



- Standard One Year Warranty
- One Year Loss and Damage included*
- Size 10A battery
- Replaceable swing-out battery door
- Gold plated battery contacts
- Switched Volume Control
- Wax removal brush
- Helpful hint booklet
- One free premium zinc air battery
- Pouch



Model MC 5000(Mini-Canal)

Charged options:

Frequency pot

Gain pot

F.B.R. pot (feedback reduction pot)

Threshold pot (if applicable)

Output Limiter pot

Variable Compression pot (if applicable)

Analog Amplifier choices:

Class A Amplifier

- Up to 35 dB H.F.A. full gain
- Up to 112dB SSPL
- 0.6 MA battery drain
- Up to 100hours of battery life with size 10A zinc air battery

Push Pull Amplifier

- Up to 45 dB H.F.A. full on gain
- Up to 120 dB SSPL
- Battery drain of 1.5 MA
- Battery life: up to 80 hours with size 10A zinc air battery

Class D Amplifier

- Up to 40 dB H.F.A. full on gain
- Up to 120 dB SSPL
- Battery drain of 0.55 MA
- Battery life: up to 120 hours with size 10A zinc air battery

Low Drain Amplifier (Class A Only)

- Up to 35 dB H.F.A. full on gain
- Up to 105 dB SSPL
- Battery drain of 0.55 MA
- Battery life: up to 120 hours with size 10A zinc air battery

AGC Amplifier

- Up to 35 dB H.F.A. full on gain
- Up to 115 dB SSPL
- Battery drain of 0.4 MA
- Battery life: up to 170 hours with size 10A zinc air battery

AGC/Class D Amplifier

- Up to 40 dB H.F.A. full on gain
- Up to 120 dB SSPL
- Battery drain of 0.55 MA
- Battery life: up to 120 hours with size 10A zinc air battery

*Toggle Switch may be substituted for a pot at no extra charge.
Battery life may vary depending on ambient noise, temperature etc.*

* A processing fee will apply: please call us at (800)322-8238, or visit our website at <http://www.prairielabs.com> for more information.